

Remote Keypad

Activate or deactivate the alarm with the keypad or from your App.

use at nighttime. Powered by lithium batteries, the These easy-to-install, stylish keypads blend naturally with any home décor.

16-buttton wireless keypads with backlighting for easy keypads feature long battery life lasting four to six years.



Key features

- 16-button backlit keypad for easy use at nighttime
- Consume power only when in operation
- Low battery detection
- Tamper protection
- Compact profile
- Communication: ZigBee

Area of use

The keypad is mounted in the entrance area – always present, easy to use. As an addition to app in case of low cellphone battery or misplaced phone.

If you have a Yale Doorman digital doorlock as a part of your security solution, you will not need the keypad.

Included in the safe4 eco-system.

Services

- Monitoring and Alarm Receiving Services from certified ARC.
- Push notification in app, Sabotage alarm.
- Manned security Services if offered by service provider.

Technical specifications

Dimensions	80mm x 116mm x 21mm
Power Source	3V, EL123AP Lithium battery x1
Battery Life	9 years (Actual battery life may vary due to device settings, operating environment and usage activity)
NFC Tag Dimensions	45mm x 25mm
NFC Tag Protocol	ISO 14443A
Operating Humidity	Up to 85% non-condensing
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Communication Protocol	ZigBee Pro Home Automation 1.2, 2.5GHz